



**TF Semiconductor
Solutions**

TFSS Gate Driver Selection Guide

Spring 2021

TFSS 200V – 250V GATE DRIVERS

Telefunken Device ID	Type/Description	Max. Offset Voltage	Sink/Source Current (typ)	Inputs	Deadtime	Ton/Toff	Rise/Fall	Package
TF1503	Half Bridge Gate Driver	250	290mA/600mA	HIN/LIN*	520ns	680ns/150ns	70ns/35ns	SOIC8(N)/PDIP8
TF1504	Half Bridge Gate Driver	250	290mA/600mA	HIN/LIN*	520ns	680ns/150ns	70ns/35ns	SOIC8(N)/PDIP9
TF1581	High Side/Low Side Gate Driver	250	1.9A/2.3A	HIN/LIN	none	180ns/220ns	40ns/20ns	SOIC8(N)
TF1584	Half Bridge Gate Driver	250	1.9A/2.3A	IN/SD*	400ns	680ns/270ns	40ns/20ns	SOIC8(N)
TF1636	3-Phase Gate Driver	250	200mA/350mA	HIN/LIN*	290ns	330ns/330ns	90ns/35ns	SOIC28(W)
TF1692	3-Phase Gate Driver	250	350mA/650mA	HIN/LIN*	290ns	500ns/500ns	50ns/30ns	SOIC28(W)
TF2003	Half Bridge Gate Driver	200	290mA/600mA	HIN/LIN*	420ns	680ns/150ns	70ns/35ns	SOIC8(N)
TF2004	Half Bridge Gate Driver	200	290mA/600mA	HIN/LIN*	420ns	680ns/150ns	70ns/35ns	SOIC8(N)
TF2005	High Side/Low Side Gate Driver	200	290mA/600mA	HIN/LIN*	none	160ns/150ns	70ns/30ns	SOIC8(N)
TF2011	High Side/Low Side Gate Driver	200	1.0A/1.0A	HIN/LIN*	none	120ns/120ns	30ns/30ns	SOIC8(N)
TF2012	High Side/Low Side Gate Driver	200	1.9A/2.3A	HIN/LIN*	none	120ns/120ns	30ns/30ns	SOIC8(N)

TFSS 600V GATE DRIVERS

Telefunken Device ID	Type/Description	Max. Offset Voltage	Sink/Source Current (typ)	Inputs	Deadtime	Ton/Toff	Rise/Fall	Package
TF2101M	High-Side/Low-Side Gate Driver	600	290mA/600mA	HIN/LIN	none	160ns/150ns	70ns/35ns	SOIC14(N)/ SOIC8(N)
TF2103M	Half-Bridge Gate Driver	600	290mA/600mA	HIN/LIN*	520ns	680ns/150ns	70ns/35ns	SOIC8(N)/ PDIP8
TF2104M	Half-Bridge Gate Driver	600	290mA/600mA	IN/SD*	520ns	680ns/150ns	70ns/35ns	SOIC8(N)/ PDIP8
TF2106M	High-Side/Low-Side Gate Driver	600	290mA/600mA	HIN/LIN	none	220ns/200ns	100ns/35ns	SOIC8(N)/ PDIP8
TF21064M	High-Side/Low-Side Gate Driver	600	290mA/600mA	HIN/LIN	none	220ns/200ns	100ns/35ns	SOIC14(N)/ PDIP14
TF2110M	High-Side/Low-Side Gate Driver	600	2.5A/2.5A	HIN/LIN	none	105ns/94ns	15ns/13ns	SOIC16(W)/ PDIP14
TF2113M	High-Side/Low-Side Gate Driver	600	2.5A/2.5A	HIN/LIN	none	105ns/94ns	15ns/13ns	SOIC16(W)/ PDIP14
TF2190M	High-Side/Low-Side Gate Driver	600	4.5A/4.5A	HIN/LIN	none	140ns/140ns	25ns/20ns	SOIC8(N)
TF21904M	High-Side/Low-Side Gate Driver	600	4.5A/4.5A	HIN/LIN	none	140ns/140ns	25ns/20ns	SOIC14(N)
TF2181M	High-Side/Low-Side Gate Driver	600	1.9A/2.3A	HIN/LIN	none	180ns/220ns	40ns/20ns	SOIC8(N)/ PDIP8
TF21814M	High-Side/Low-Side Gate Driver	600	1.9A/2.3A	HIN/LIN	none	180ns/220ns	40ns/20ns	SOIC14(N)/ PDIP14
TF2108	Half-Bridge Gate Driver	600	290mA/600mA	HIN/LIN*	540ns	220ns/200ns	100ns/35ns	SOIC8(N)/ PDIP8
TF21084	Half-Bridge Gate Driver	600	290mA/600mA	HIN/LIN*	540ns - 5ms	220ns/200ns	100ns/35ns	SOIC14(N)/ PDIP14
TF2184M	Half-Bridge Gate Driver	600	1.9A/2.3A	IN/SD*	400ns	680ns/270ns	40ns/20ns	SOIC8(N)/ PDIP
TF21844M	Half-Bridge Gate Driver	600	1.9A/2.3A	IN/SD*	400ns - 5ms	680ns/270ns	40ns/20ns	SOIC14(N)/ PDIP14
TF21364M	3-Phase Gate Driver	600	200mA/350mA	HIN*/LIN*	290ns	330ns/330ns	90ns/35ns	SOIC28(W)
TF2136M	3-Phase Gate Driver	600	200mA/350mA	HIN/LIN*	290ns	330ns/330ns	90ns/35ns	SOIC28(W)
TF2304M	Half Bridge Gate Driver	600	290mA/600mA	HIN/LIN*	100ns	150ns/150ns	70ns/35ns	SOIC8(N)
TF23892M	3-Phase Gate Driver	600	350mA/650mA	HIN/LIN*	290ns	500ns/500ns	50ns/30ns	SOIC28(W)

TFSS CONTACT INFORMATION

Sales Contacts	Region	Telephone Number	E-mail
Duke Walton	Worldwide	+(1) 916-580-5805	duke.walton@tfsemi.com
Felix Cai	Asia	+86-1351-102-3160	felix.cai@tfsemi.com
Applications Support			
Keith Spaulding	Worldwide	+(1) 603-343-4499	keith.spaulding@tfsemi.com
Support	Worldwide	+(1) 916-865-4961	support@tfsemi.com
Customer Service			
Customer Service Hotline	Worldwide	+(1) 916-865-4961	support@tfsemi.com
Quality			
Ken Nowak	Worldwide	+(1) 603-343-1952	ken.nowak@tfsemi.com
Supply Chain Management			
Daniel Xu	Worldwide	+(1) 916-865-4961	daniel.xu@tfsemi.com

<p>NORTH AMERICA 1430 Blue Oaks Boulevard, Suite 288 Roseville, CA 95747, USA Tel: +(1) 916-865-4961</p>	<p>ASIA Tel: + 86-1351-102-3160</p>
--	---

Important Notice

TF Semiconductor Solutions (TFSS) PRODUCTS ARE NEITHER DESIGNED NOR INTENDED FOR USE IN MILITARY AND/OR AEROSPACE, AUTOMOTIVE OR MEDICAL DEVICES OR SYSTEMS UNLESS THE SPECIFIC TFSS PRODUCTS ARE SPECIFICALLY DESIGNATED BY TFSS FOR SUCH USE. BUYERS ACKNOWLEDGE AND AGREE THAT ANY SUCH USE OF TFSS PRODUCTS WHICH TFSS HAS NOT DESIGNATED FOR USE IN MILITARY AND/OR AEROSPACE, AUTOMOTIVE OR MEDICAL DEVICES OR SYSTEMS IS SOLELY AT THE BUYER'S RISK.

TFSS assumes no liability for application assistance or customer product design. Customers are responsible for their products and applications using TFSS products.

Resale of TFSS products or services with statements different from or beyond the parameters stated by TFSS for that product or service voids all express and any implied warranties for the associated TFSS product or service. TFSS is not responsible or liable for any such statements.

©2021 TFSS. All Rights Reserved. Information and data in this document are owned by TFSS wholly and may not be edited, reproduced, or redistributed in any way without the express written consent from TFSS.